
BRUMBERG

LED converter 500 mA, TunableWhite, DALI-DT8 dimmable, 15 W

Article no. 17821010

Light. For Generations.







Tender

LED converter 500 mA, TunableWhite, DALI-DT8 dimmable, 15 W, , Rectangular. This control gear meets the requirements for safety lighting systems in accordance with DIN EN 50172 VDE 0108-100:2005-01. This converter is protected against overvoltage and short circuits as well as thermal and electrical overload by fuses. The input and output terminals are suitable for cables with a cross-section of 0.75-1.5 mm². Material: Plastic, Degree of protection: according to DIN EN 60529 IP20, Protection class: (EN 61140) II, Current: 500 mA, Voltage: 230V AC 50Hz, Power: 15 W, Dimmable: Yes, Control: DALI-2.

Article data	
Article no.	17821010
Short description	LED converter 500 mA, TunableWhite, DALI-DT8 dimmable, 15 W
Material	Plastic
Shape	Rectangular
Length	178 mm
Width	46 mm
Hight	22 mm
Weight	0.122 kg
stamp	ENEC
Conformance	CE

BRUMBERG

LED converter 500 mA, TunableWhite, DALI-DT8 dimmable, 15 W

Article no. 17821010

Light. For Generations.

Operating technology of driver	
AC nominal voltage min	200 V
AC nominal voltage max	240 V
Frequency min	50 Hz
Frequency max	60 Hz
Protection class	
Degree of protection	IP20
Power min	3 W
Power	15 W
Starting current	6,16
Suitable for emergency lighting	No
measure point (tc)	85 °C
Version	without
Power factor	0.95
Output voltage max	30.00 V
Output voltage min	5.00 V
Control	DALI-2 , DALI-DT8
Number of poles	4
Flicker-free	Yes
Enviroment temprature (ta)	-20 °C bis +45 °C
Measure point (tc)	max. +85 °C
Output current	500 mA

Packing data	
Gross weight	0.145 kg
Length of packaging	45 mm
Packaging width	35 mm
Packaging hight	190 mm
	This product must not be disposed of with household waste. You are obliged, to dispose of such electrical waste separately.
Disposal at end of life	By disposing of electrical waste and other old or defective electronics separately, you support recycling or other forms of re-use. In that way you help to take care and to avoid that harmful substances get into the environment.