


IDL 70.2027.2500

IndiLine (1xLED 28W 827/2700K 2100lm)

— C0/C180 cd / 1000 lm - - - C90/C270



	C0	C90	C180	C270
0°	30	30	30	30
30°	0	25	102	27
60°	0	17	198	18
90°	0	1	319	2
120°	0	6	411	6
150°	0	1	47	2
180°	0	0	0	0
cd / 1000 lm				

LDC unsuitable for cone representation.
Asymmetric LDC.

η Efficiency	LED 75 lm/W
Direct/Indirect	↓ 39% / ↑ 61%
System Power	28 W
UGR Reflection factors	X=4H, Y=8H 70/50/20
UGR C0/C180	<10.0
UGR C90/C270	14.8
CIE Flux Codes Ra/CRI	15 37 65 39 100 >80